

# JDYX8.E355868 - Fuses, Supplemental Certified for Canada - Component

## Fuses, Supplemental Certified for Canada - Component

**ADVANCED SURGETECH MATERIALS LTD**

Floor 6 to 9, building 13, No. 7, Houjie Science and Technology Avenue, Houjie Town  
Dongguan, Guangdong 523946 China

E355868

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
<b>Supplemental fuses: filled-tube</b>				
<b>HV610, HV620, HV630, HV640, HV650, MV610, MV620 or MV630, followed by ".", followed by 0.1 to 50.</b>	6.3 x 31.75 (0.25 x 1.25)	0.1- 50	250Vac	1000
		0.1- 30	660Vac	1000
		0.1- 30	660Vdc	1000
		0.1- 12	600Vdc	10000
		0.1- 12	1000Vdc	10000
		0.1- 50	150Vdc	1000
		0.1- 12	600Vac	10000
		0.1- 12	1000Vac	10000
		0.1- 30	400Vac	1000
		0.1- 30	600Vac	1000
		0.1- 30	630Vac	1000
		0.1- 30	400Vdc	1000
		0.1- 30	600Vdc	1000
		0.1- 30	630Vdc	1000
		0.1- 12	1000Vdc	10000

### Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		0.1-12	300Vdc	10000
<b>Supplemental fuses: filled-tube, cartridge enclosed</b>				
<b>A062502, A062503, A062504, A062505, A062506 or A062507, followed by -, followed by 5, 6.3, 7, 8, 10, 12, 15, 20, 25 or 30.</b>	6.3 x 24.3 (0.25 x 0.96)	5-30	250Vac	1500
		5-30	420Vdc	300
<b>HV510, HV520, HV530, A052001, A052002 , , followed by '.', followed by ampere 0.1 - 20.</b>	5.2 x 20 (0.20 x 0.79)	0.1-20	600Vac	200
		0.1-20	500Vac	200
		0.1-20	500Vdc	300
		0.1-10	400Vdc	2000
		0.1-1	600Vac	1000
		0.1-20	420Vac	200
		0.1-20	400Vdc	300
		0.1-20	420Vdc	300
		0.1-20	450Vdc	300
<b>HV638.xx, HV63801.xx or HV63802.xx , xx denoting Any digital numbers indicate ampere rating.</b>	6.35 x 38.2 (0.25 x 1.50)	1-6	960Vac	400
		1-6	600Vac	10k
		1-6	480Vac	10k
<b>HV660, HV670, HV680, HV681, HV682, HV683 or HV690, followed by " . " , followed by 0.1-30</b>	6.4 x 31.75 (0.25 x 1.25)	0.1-30	500Vac	1000
		0.1-30	500Vdc	1000
		0.1-30	500Vac	30K
		0.1-30	500Vdc	20K
		0.1-30	400Vac	1000

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

0.1-30 500Vdc 20K

0.1-30 400Vac 1000

		0.1-30	420Vdc	1000
		0.1-30	420Vac	30k
		0.1-30	420Vdc	20k
		0.1-30	300Vdc	20k
<b>Supplemental fuses: filled-tube, surface mount</b>				
<b>1040 100, 1040 110, 1040 120 or 1040 130 , followed by '.', followed by ampere 0.5-6.3.</b>	12 x 2.6 x 4.4 (0.47 x 0.10 x 0.17)	0.5-6.3	250Vac	150
		0.5-6.3	350Vac	150
		0.5-6.3	250Vdc	100
		0.5-6.3	350Vdc	100
<b>Supplemental fuses: filled-tube, surface mount, cartridge enclosed "A114501/2/3/4/5/8, APCC, APCB"</b>				
<b>A114501 , A114502, A114503, A114504, A114505, A114508, APCC, APCB, followed by '.', followed by ampere 0.2-5.</b>	11 x 5 x 5 (0.43 x 0.20 x 0.20)	0.2-5	125Vac	100
		0.2-5	250Vac	100
		0.2-5	350Vac	100
		0.2-5	125Vac	10000
		0.2-5	420Vdc	100
		0.2-5	450Vdc	100
		0.2-5	500Vdc	100
		0.2-5	125Vdc	1500
		0.2-5	250Vdc	1500
		0.2-5	350Vdc	1500
		0.2-5	250Vdc	6000
		0.2-5	350Vdc	6000
		0.2-5	420Vdc	6000
		0.2-5	450Vdc	6000
<b>Supplemental fuses: filled-tube, surface mount, cartridge enclosed "A324501, A324502, A324503, A324504, A324505"</b>				

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

0.2-5 450Vdc 6000  
[Cookies Settings](#)

[Accept All Cookies](#)

<b>A324501 , A324502, A324503, A324504, A324505, A324508, followed by '.', followed by ampere 0.2-3.</b>	32 x 5 x 5 (1.26 x 0.20 x 0.20)	0.2-3	500Vac	10000
		0.2-3	750Vac	10000
		0.2-3	800Vac	10000
		0.2-3	500Vdc	10000
		0.2-3	750Vdc	10000
		0.2-3	800Vdc	10000
		0.2-3	1000Vdc	10000

**Supplemental fuses: filled-tube, surface mount, cartridge enclosed**

<b>A1350 , followed by 001-008, followed by ".", followed by ampere 0.5-7.5, and followed by 2 digits, letters or blank</b>	13.2 x 5.05 x 5.05 (0.52 x 0.20 x 0.20)	0.5- 7.5	350Vac	100
		0.5- 7.5	250Vac	100
		0.5- 7.5	125Vac	100
		0.5- 7.5	400Vdc	200
		0.5- 7.5	350Vdc	200
		0.5- 7.5	250Vdc	200
		0.5- 7.5	125Vdc	200
		0.5-5	500Vdc	100
		0.5-5	400Vdc	100
		0.5-5	350Vdc	100
		0.5-5	250Vdc	100
		0.5-5	125Vdc	100
		0.5- 3.15	600Vdc	100

**Supplemental fuses: pigtail leads, filled-tube**

<b>HV610, HV620, HV630, HV640, HV650, MV610, MV620 or MV630, followed by ".", followed by ampere 0.1 to 50, followed by P .</b>	6.3 x 31.75 (0.25 x 1.25)	0.1- 50	250Vac	1000
		0.1- 30	660Vac	1000

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		0.1-30	660Vdc	1000
		0.1-12	600Vdc	10000
		0.1-12	1000Vdc	10000
		0.1-50	150Vdc	1000
		0.1-12	600Vac	10000
		0.1-12	1000Vac	10000
		0.1-30	400Vac	1000
		0.1-30	600Vac	1000
		0.1-30	630Vac	1000
		0.1-30	400Vdc	1000
		0.1-30	600Vdc	1000
		0.1-30	630Vdc	1000
		0.1-12	300Vac	10000
		0.1-12	300Vdc	10000

**Supplemental fuses: pigtail leads, filled-tube, cartridge enclosed**

<b>62 020 , followed by '.', followed by ampere 0.1-50 and may followed by suffix P</b>	6.76 x 26.5 (0.27 x 1.04)	0.1-20	250Vac	10000
		0.1-20	400Vdc	2000
		0.1-30	400Vdc	300
		0.1-50	75Vdc	2500
		0.1-50	85Vdc	2500
<b>62 021 , followed by '.', followed by ampere 0.1-50 and may followed by suffix P</b>	6.76 x 26.5 (0.27 x 1.04)	0.1-20	250Vac	10000
		0.1-20	400Vdc	2000

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

**Cookies Settings**

**Accept All Cookies**

		0.1-30	400Vdc	300
		0.1-50	75Vdc	2500
		0.1-50	85Vdc	2500
<b>62 022 , followed by '.', followed by ampere 0.1-50 and may followed by suffix P</b>	6.76 x 26.5 (0.27 x 1.04)	0.1-20	250Vac	10000
		0.1-20	400Vdc	2000
		0.1-30	400Vdc	300
		0.1-50	75Vdc	2500
		0.1-50	85Vdc	2500
<b>62 720 , followed by '.', followed by ampere 0.1-50 and may followed by suffix P</b>	6.76 x 26.5 (0.27 x 1.04)	0.1-20	250Vac	10000
		0.1-20	400Vdc	2000
		0.1-30	400Vdc	300
		0.1-50	75Vdc	2500
		0.1-50	85Vdc	2500
<b>A0501-xx - where xx is number indicating the ampere rating</b>	-	0.1-25	300Vac	750
		0.1-25	250Vac	750
		0.1-25	420Vac	300
		0.1-25	420Vdc	300
		0.1-25	300Vdc	1000
		0.1-16	300Vac	1500
		0.1-16	300Vac	750
		0.1-16	250Vac	1500
		0.1-16	250Vac	750

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

<b>A0502-xx - where xx is number indicating the ampere rating</b>	-	0.1-25	300Vac	750
		0.1-25	250Vac	750
		0.1-25	420Vac	300
		0.1-25	420Vdc	300
		0.1-25	300Vdc	1000
		0.1-16	300Vac	1500
		0.1-16	300Vac	750
		0.1-16	250Vac	1500
		0.1-16	250Vac	750
<b>A0503-xx - where xx is number indicating the ampere rating</b>	-	0.1-25	300Vac	750
		0.1-25	250Vac	750
		0.1-25	420Vac	300
		0.1-25	420Vdc	300
		0.1-25	300Vdc	1000
		0.1-16	300Vac	1500
		0.1-16	300Vac	750
		0.1-16	250Vac	1500
		0.1-16	250Vac	750
<b>A062502, A062503, A062504, A062505, A062506 or A062507 , followed by -, followed by 5, 6.3, 7, 8, 10, 12, 15, 20, 25 or 30, followed by P, P-L or BT.</b>	6.76 x 25.4 (0.27 x 1.00)	5-30	250Vac	1500
		5-30	420Vdc	300
<b>HV510, HV520, HV530, A052001, A052002 , followed by '.', followed by 0.1 - 20, followed by P.</b>	5.54 x 21.1 (0.22 x 0.83)	0.1-20	600Vac	200
		0.1-20	500Vac	200

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Accept All Cookies

0.1-20

		0.1-20	500Vdc	300
		0.1-10	400Vdc	2000
		0.1-1	600Vac	1000
		0.1-20	420Vac	200
		0.1-20	400Vdc	300
		0.1-20	420Vdc	300
		0.1-20	450Vdc	300
<b>HV638.xx, HV63801.xx or HV63802.xx, followed by suffix P, P-L, or P-SXL, xx denoting Any digital numbers indicate ampere rating.</b>	6.76 x 39.2 (0.27 x 1.54)	1-6	960Vac	400
		1-6	600Vac	10k
		1-6	480Vac	10k
<b>HV660, HV670, HV680, HV681, HV682, HV683 or HV690, followed by ':', followed by 0.1-30, followed by P.</b>	6.76 x 32.8 (0.27 x 1.29)	0.1-30	500Vac	1000
		0.1-30	500Vdc	1000
		0.1-30	500Vac	30K
		0.1-30	500Vdc	20K
		0.1-30	420Vac	1000
		0.1-30	420Vdc	1000
		0.1-30	420Vac	30k
		0.1-30	420Vdc	20K
		0.1-30	300Vdc	20K
<b>MV510, MV520, MV530, MV540 or MV550, followed by ':', followed by ampere 0.1-30.</b>	5.54 x 21.1 (0.22 x 0.83)	0.1-10	300Vac	3000
		0.1-10	300Vdc	3000

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

**Cookies Settings**

---

**Accept All Cookies**



		0.1-30	300Vdc	300
		0.1-30	300Vac	300
<b>MV510, MV520, MV530, MV540 or MV550, , followed by '.', followed by ampere 0.1-30, followed by suffix P.</b>	5.54 x 21.1 (0.22 x 0.83)	0.1-10	300Vac	3000
		0.1-10	300Vdc	3000
		0.1-30	300Vdc	300
		0.1-30	300Vac	300
<b>Supplemental fuses: surface mount</b>				
<b>24 148, PB02, PB03, PB04 or PB05 , followed by '.', followed by ampere 0.2-50.</b>	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.2-2	250Vac	100
		0.2-15	125Vac	50
		0.2-15	125Vdc	50
		0.2-15	72Vdc	50
		0.2-30	72Vdc	500
		0.2-50	72Vdc	500
		0.2-50	63Vdc	500
		0.2-50	32Vdc	500
		0.2-50	24Vdc	500
<b>PB01 , followed by '0', followed by ampere 0.2-50.</b>	6.1 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.2-2	250Vac	100
		0.2-15	125Vac	50
		0.2-15	125Vdc	50
		0.2-15	72Vdc	50
		0.2-30	72Vdc	500
		0.2-50	72Vdc	500
		0.2-50	63Vdc	500
		0.2-50	32Vdc	500
		0.2-50	24Vdc	500

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

0.2-15 125Vac 50  
**Cookie Settings**

0.2-15 125Vdc 50  
**Accept All Cookies**

		0.2-15	72Vdc	50
		0.2-30	72Vdc	500
		0.2-50	72Vdc	500
		0.2-50	63Vdc	500
		0.2-50	32Vdc	500
		0.2-50	24Vdc	500
<b>Supplemental fuses: surface mount, cartridge enclosed</b>				
<b>40 100, 40 110 and 40 112</b>	11 x 4 x 4 (0.43 x 0.16 x 0.16)	0.1-5	125Vac	150
		5.5-40	125Vac	150
		0.1-5	250Vac	150
		5.5-40	250Vac	150
		45-60	125Vac	250
		0.1-5	125Vdc	10k
		0.1-5	125Vdc	150
		0.1-5	250Vdc	150
		5.5-15	125Vdc	10k
		5.5-40	72Vdc	500
		45-60	60Vdc	500
		5.5-40	32Vdc	1000
		45-60	32Vdc	1000
		0.1-3.15	350Vdc	1500
		0.1-3.15	600Vdc	100
		0.1-3.15	500Vdc	100
		0.1-3.15	100Vdc	100

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings  
 Accept All Cookies

		0.1-3.15	350Vdc	100
		0.1-3.15	400Vdc	50
		0.1-3.15	600Vac	100
		0.1-3.15	350Vac	100
<b>PC01</b>	11 x 4 x 4 (0.43 x 0.16 x 0.16)	0.1-5	125Vac	150
		5.5-40	125Vac	150
		0.1-5	250Vac	150
		5.5-40	250Vac	150
		45-60	125Vac	250
		0.1-5	125Vdc	10k
		0.1-5	125Vdc	150
		0.1-5	250Vdc	150
		5.5-15	125Vdc	10k
		5.5-40	72Vdc	500
		45-60	60Vdc	500
		5.5-40	32Vdc	1000
		45-60	32Vdc	1000
		0.1-3.15	350Vdc	1500
		0.1-3.15	600Vdc	100
		0.1-3.15	500Vdc	100
		0.1-3.15	400Vdc	100
		0.1-3.15	350Vdc	100
		0.1-3.15	400Vdc	50
		0.1-3.15	600Vac	100
		0.1-3.15	600Vac	100

### Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		0.1-3.15	350Vac	100
<b>Supplemental micro fuses</b>				
<b>1025FA</b>	2.77 x 2.77 x 10.29 (0.11 x 0.11 x 0.41)	0.25-10	250Vac	50
		0.25-10	125Vdc	50
		12-15	250Vac	50
		12-15	60Vdc	50
<b>1025TD</b>	2.77 x 2.77 x 10.29 (0.11 x 0.11 x 0.41)	0.25-5	250Vac	50
		0.25-5	125Vdc	50
<b>24 100</b>	2.6 x 2.6 x 6.1 (0.10 x 0.10 x 0.24)	2-5	125Vac	50
		2-10	125Vdc	300
		6.3-6.3	125Vac	63
		7.0-7.0	125Vac	70
		8.0-8.0	125Vac	80
		10.0-10.0	125Vac	100
		12-15	125Vac	50
		12-15	125Vdc	300
<b>24 109, 24 113 and 24 122</b>	6.5 x 2.8 x 2.8 (0.26 x 0.11 x 0.11)	0.25-7	125Vac	100

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		0.25-7	250Vac	100
		0.25-7	350Vac	50
		0.25-7	125Vdc	50
<b>24 110</b>	6.5 x 2.8 x 2.8 (0.26 x 0.11 x 0.11)	0.25-7	125Vac	100
		0.25-7	250Vac	100
		0.25-7	350Vac	50
		0.25-7	125Vdc	50
<b>6125FA</b>	2.72 x 2.72 x 6.1 (0.11 x 0.11 x 0.24)	0.5-15	125Vac	50
		0.5-15	32Vdc	300
		0.5-15	72Vdc	50
<b>6125TD</b>	2.72 x 2.72 x 6.1 (0.11 x 0.11 x 0.24)	0.5-7	125Vac	50
		0.5-7	60Vdc	50
<b>TCP/1025TC</b>	2.77 x 2.77 x 10.29 (0.11 x 0.11 x 0.41)	0.5-2	250Vac	50
		0.5-2	600Vac	60
<b>Supplemental micro fuses: surface mount</b>				
<b>04 100 , 04 110, 04 111, 04 113, 04 010, 04 020, 04 022, followed by '.', followed by ampere 0.1-4.</b>	1.1 x 0.5 x 0.4 (0.04 x 0.02 x 0.02)	0.1-4	32Vdc	35

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

0.1-4
32Vdc
35

Accept All Cookies

<b>06 100, 06 110, 06 120, 06 122, 06 010 or 06 020 , followed by ':' , followed by ampere 0-8.</b>	1.6 x 0.81 x 0.65 (0.06 x 0.03 x 0.03)	0.1-5	63Vdc	50
		0.1-8	32Vdc	50
<b>12 100, 12 110, 12 111, 12 113, 12 010, 12 020 or 12 022, followed by ':' , followed by ampere rating 0.1-50, followed by blank, LW, LR, LV or any other alphanumeric.</b>	3.2 x 1.6 x 0.65 (0.13 x 0.06 x 0.03)	0.1-30	24Vdc	300
		0.1-7	32Vdc	50
		0.1-3	125Vdc	50
		0.1-5	125Vac	50
		0.1-30	36Vdc	150
		0.1-30	32Vdc	150
		0.1-20	48Vdc	150
		0.1-7	72Vdc	50
		0.1-7	63Vdc	50
		0.1-50	24Vdc	200
		0.1-50	32Vdc	200
		0.1-50	36Vdc	200
<b>Supplemental micro fuses: surface mount, cartridge enclosed</b>				
<b>PB06, PB07, PB08, PB09, 1140100, 1140110 followed by ampere 0.2A, 0.25A, 0.375A, 0.5A, 0.75A, 1A, 1.5A, 2A, 2.5A, 3A, 3.5A, 4A, 5A, 6A, 7A, 8A, 10A, 12A, 15A, 20A, 25A or 30A, followed by '0' , followed by ampere 0.2A-30A.</b>	9.9 x 1.7 x 3.14 (0.39 x 0.07 x 0.12)	0.2-25	250Vac	150
		0.2-25	125Vac	150
		0.2-25	125Vdc	150
		0.2-30	80Vdc	800
		0.2-30	72Vdc	800
		0.2-30	63Vdc	800

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

Cookies Settings

Accept All Cookies

		0.2-30	32Vdc	800
--	--	--------	-------	-----

Marking: Company name or trademark  ,  ,  , model designation and the Recognized Component Mark for Canada, .

Last Updated on 2022-07-04

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."

## Cookies on UL Solutions

We use cookies to personalize content and ads, to provide social media features and to analyze our traffic. We also share information about your use of our site with our social media, advertising and analytics partners. [Learn more](#)

[Cookies Settings](#)

[Accept All Cookies](#)